



SYNTECH
POWER & LIGHT

**5W and 7.5W CFM-R CCT
Adjustable Series - 125mm
OD**



INSTALLATION GUIDE




SYNTECH

POWER & LIGHT


Installation Instructions

1. Ensure mains power is disconnected prior to installation process
2. Remove luminaire from protective packaging and discard packaging responsibly.
3. If product is being used in a retro-fit installation, check existing cut-out size meets specified dimensions and adjust if required. (For new installations cut mounting hole as specified below)
4. Insert new luminaire into existing or newly prepared cavity as per diagram.
5. Insert three pin plug into ceiling mounted G.P.O (General Power Outlet)

INSTALLATION PROCEDURES




1. Existing or newly prepared ceiling hole should be cut to 100mm dia (max)



2. Push mounting clips back against the body of the new luminaire and insert into mounting hole.

3. Insert 3 pin plug into roof mounted G.P.O (General Power Outlet)
Reconnect Mains Power



Note: Syntech International strongly recommends this product be installed by a licensed electrician