



**SYNTECH**  
**POWER & LIGHT**

## **RGS Series 2 Rectangular LED**



# **INSTALLATION GUIDE**




# SYNTECH

## POWER & LIGHT

### Installation Instructions

1. Ensure mains power is disconnected prior to installation process
2. Remove luminaire from protective packaging and discard packaging responsibly.
3. If product is being used in a retro-fit installation, check existing hole size meets specified dimensions and adjust if required. (For new installations cut mounting hole as specified below)
4. Insert new luminaire into existing or newly prepared cavity as per diagram.
5. Insert three pin plug into ceiling mounted G.P.O (General Power Outlet)
6. Adjust beam angle as required then reconnect power .

#### INSTALLATION PROCEDURES




1. Existing or newly prepared ceiling hole should be cut to 227mm x 130mm

2. Push mounting clips back against the body of the new luminaire and insert into mounting hole.

3. Insert 3 pin plug into roof mounted G.P.O (General Power Outlet)

Reconnect Mains Power



Note: Syntech International strongly recommends this product be installed by a licensed electrician